

HTTP-Request Shelly PLUS i4

Shelly PLUS i4

HTTP-Request with Original-Firmware:

Enter in the address bar of the browser:

- Complete state **Shelly PLUS i4:**

Code

```
http://192.168.xxx.xxx/rpc/Sys.GetStatus
```

- Input state (I1 - I4) **Shelly PLUS i4:**

Code

```
http://192.168.xxx.xxx/rpc/Input.GetStatus?id=0
```

input assignment: input 1: "0", input 2: "1", input 3: "2", input 4: "3"; adjust accordingly!

- Input config (I1 - I4) **Shelly PLUS i4:**

Code

```
http://192.168.xxx.xxx/rpc/Input.GetConfig?id=0
```

input assignment: input 1: "0", input 2: "1", input 3: "2", input 4: "3"; adjust accordingly!

- Device info Shelly PLUS i4:

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetDeviceInfo
```

- Update Shelly PLUS i4:

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update
```

Optional: Beta-Update

Code

`http://192.168.xxx.xxx/rpc/Shelly.Update?stage=beta`

- Reboot Shelly PLUS i4:

Code

`http://192.168.xxx.xxx/rpc/Shelly.Reboot`

- Reset [Shelly PLUS i4](#):

Code

`http://192.168.xxx.xxx/rpc/Shelly.FactoryReset`

- WiFi-State Shelly PLUS i4:

Code

`http://192.168.xxx.xxx/rpc/WiFi.GetStatus`

- LAN-State Shelly PLUS i4:

Code

`http://192.168.xxx.xxx/rpc/Eth.GetStatus`

- Bluetooth-State Shelly PLUS i4:

Code

`http://192.168.xxx.xxx/rpc/BLE.GetStatus`

- Cloud State Shelly PLUS i4:

Code

`http://192.168.xxx.xxx/rpc/Cloud.GetStatus`

Shelly API-Documentation: <https://shelly-api-docs.shelly.cloud/gen2/>