

# HTTP-Request Shelly PLUS 1

Shelly PLUS 1

## HTTP-Request mit Original-Firmware:

Eingabe in die Adressleiste des Browsers:

- Kompletstatus [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetStatus
```

- Status Schalter [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Switch.GetStatus?id=0
```

- Schalten [Shelly PLUS 1](#) Relais EIN:

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=true  
oder  
http://192.168.xxx.xxx/relay/0?turn=on
```

- Schalten [Shelly PLUS 1](#) Relais AUS:

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=false  
oder  
http://192.168.xxx.xxx/relay/0?turn=off
```

- Umschalten [Shelly PLUS 1](#) Relais EIN/AUS:

Code

```
http://192.168.xxx.xxx/rpc/Switch.toggle?id=0  
oder  
http://192.168.xxx.xxx/relay/0?turn=toggle
```

- Schalten [Shelly PLUS 1](#) Relais EIN mit Timer in s:

Code

```
http://192.168.xxx.xxx/relay/0?turn=on&timer=30
```

- Schalten [Shelly PLUS 1](#) Relais AUS mit Timer in s:

Code

```
http://192.168.xxx.xxx/relay/0?turn=off&timer=30
```

- Status Eingang [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Input.GetStatus?id=0
```

- Konfiguration Eingang [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Input.GetConfig?id=0
```

1. switch
2. button

- Geräteinfo [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetDeviceInfo
```

- Update [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update
```

Optional: Beta-Update

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update?stage=beta
```

- Reboot [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Reboot
```

- Reset [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.FactoryReset
```

- [WLAN-Status](#) [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/WiFi.GetStatus
```

- LAN-Status [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Eth.GetStatus
```

- Bluetooth-Status [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/BLE.GetStatus
```

- Cloud Status [Shelly PLUS 1](#):

Code

```
http://192.168.xxx.xxx/rpc/Cloud.GetStatus
```

Shelly API-Dokumentation: <https://shelly-api-docs.shelly.cloud/gen2/>