

HTTP-Request Shelly PLUS 1PM

HTTP-Request Shelly PLUS 1PM

HTTP-Request with Original-Firmware:

Enter in the address bar of the browser:

- Complete state [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetStatus
```

- Switch [Shelly PLUS 1PM](#) Relay ON:

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=true  
or  
http://192.168.xxx.xxx/relay/0?turn=on
```

- Switch [Shelly PLUS 1PM](#) Relay OFF:

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=false  
or  
http://192.168.xxx.xxx/relay/0?turn=off
```

- Switch [Shelly PLUS 1PM](#) Relay TOGGLE:

Code

```
http://192.168.xxx.xxx/rpc/Switch.toggle?id=0  
or  
http://192.168.xxx.xxx/relay/0?turn=toggle
```

- Switch [Shelly PLUS 1PM](#) Relay ON with timer in s:

Code

```
http://192.168.xxx.xxx/relay/0?turn=on&timer=30
```

- Switch [Shelly PLUS 1PM](#) Relay OFF with timer in s:

Code

```
http://192.168.xxx.xxx/relay/0?turn=off&timer=30
```

- Input state [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Input.GetStatus?id=0
```

- Input config [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Input.GetConfig?id=0
```

1. switch
2. button

- Device info [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetDeviceInfo
```

- Update [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update
```

Optional: Beta-Update

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update?stage=beta
```

- Reboot [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Reboot
```

- Reset [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Shelly.FactoryReset
```

- WiFi-State [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/WiFi.GetStatus
```

- LAN-State [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Eth.GetStatus
```

- Bluetooth-State [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/BLE.GetStatus
```

- Cloud State [Shelly PLUS 1PM](#):

Code

```
http://192.168.xxx.xxx/rpc/Cloud.GetStatus
```

Shelly API-Documentation: <https://shelly-api-docs.shelly.cloud/gen2/>