

# HTTP-Request - Shelly PRO 1

Shelly PRO 1

## HTTP-Request with Original-Firmware:

Enter in the address bar of the browser:

- Complete state [Shelly PRO 1](#):

### CODE

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetStatus
```

- Switch [Shelly PRO 1](#) Relay ON:

### CODE

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=true  
or  
http://192.168.xxx.xxx/relay/0?turn=on
```

- Switch [Shelly PRO 1](#) Relay OFF:

### CODE

Code

```
http://192.168.xxx.xxx/rpc/Switch.Set?id=0&on=false  
or  
http://192.168.xxx.xxx/relay/0?turn=off
```

- Switch [Shelly PRO 1](#) Relay TOGGLE:

### CODE

Code

```
http://192.168.xxx.xxx/rpc/Switch.toggle?id=0  
or  
http://192.168.xxx.xxx/relay/0?turn=toggle
```

- Switch [Shelly PRO 1](#) Relay ON with timer in s:

## CODE

Code

```
http://192.168.xxx.xxx/relay/0?turn=on&timer=30
```

- Switch [Shelly PRO 1](#) Relay OFF with timer in s:

## CODE

Code

```
http://192.168.xxx.xxx/relay/0?turn=off&timer=30
```

- Input state [Shelly PRO 1](#):

## CODE

Code

```
http://192.168.xxx.xxx/rpc/Input.GetStatus?id=0
```

- Input config [Shelly PRO 1](#):

## CODE

Code

```
http://192.168.xxx.xxx/rpc/Input.GetConfig?id=0
```

- Device info [Shelly PRO 1](#):

## CODE

Code

```
http://192.168.xxx.xxx/rpc/Shelly.GetDeviceInfo
```

- Update [Shelly PRO 1](#):

## CODE

Code

```
http://192.168.xxx.xxx/rpc/Shelly.Update
```

Optional: Beta-Update

**CODE**

Code

`http://192.168.xxx.xxx/rpc/Shelly.Update?stage=beta`

- Reboot [Shelly PRO 1](#):

**CODE**

Code

`http://192.168.xxx.xxx/rpc/Shelly.Reboot`

- Reset [Shelly PRO 1](#):

**CODE**

Code

`http://192.168.xxx.xxx/rpc/Shelly.FactoryReset`

- WiFi-State [Shelly PRO 1](#):

**CODE**

Code

`http://192.168.xxx.xxx/rpc/WiFi.GetStatus`

- LAN-State [Shelly PRO 1](#):

**CODE**

Code

`http://192.168.xxx.xxx/rpc/Eth.GetStatus`

- Bluetooth-State [Shelly PRO 1](#):

**CODE**

Code

`http://192.168.xxx.xxx/rpc/BLE.GetStatus`

- Cloud State [Shelly PRO 1](#):

## **CODE**

Code

`http://192.168.xxx.xxx/rpc/Cloud.GetStatus`

Shelly API-Documentation: <https://shelly-api-docs.shelly.cloud/gen2/>